## NSN 5925-01-233-5682

Circuit Breaker - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5925-01-233-5682

| Body Style:  |       |
|--|-------|
| Rectangular dimensional envelope                                     |       |
| Overall Length:  |       |
| 15.500 inches  |       |
| Overall Height:  |       |
| 6.000 inches   |       |
| Overall Width:   |       |
| 9.000 inches   |       |
| Case Material:   |       |
| Plastic  |       |
| Unthreaded Mounting Hole Diameter:                                   |       |
| 0.250 inches   |       |
| Fragility Factor:  |       |
| Moderately rugged  |       |
| Pole Quantity:   |       |
| 3  |       |
| Arc Quenching Method:  |       |
| Magnetic blowout   |       |
| Mounting Facility Type And Quantity:                                 |       |
| 4 unthreaded hole  |       |
| Storage Type:  |       |
| General purpose warehouse  |       |
| Features Provided:   |       |
| Adjustable trip release  |       |
| Maximum Continuous Load Current Rating Per Pole:                     |       |
| 300.0 amperes ac all locations and 300.0 amperes dc all locations    |       |
| Operating Voltage Type And Rating Per Pole In Volts:                 |       |
| 500.0 ac all locations and 250.0 dc all locations                    |       |
| Maximum Interrupting Capacity Current Type And Rating Per Pole In    | Amps: |
| 20000.0 ac all locations and 15000.0 dc all locations                |       |
| Circuit Protection Type:   |       |
| Overcurrent all locations  |       |
| Trip Release Method:   |       |
| Thermal-magnetic all locations                                       |       |
| Trip Release Characteristic:   |       |
| Instantaneous all locations  |       |
| Ultimate Trip Rating Of Continuous Current Rating Per Pole In Percen | ıt:   |
| 125.0 all locations  |       |
| Reset Method:  |       |
| Manual   |       |
| Main Contact Tripping Mechanism Type:                                |       |
|  |       |

Trip free

## NSN 5925-01-233-5682

Circuit Breaker - Page 2 of 2

