NSN 5950-00-681-2096

Power Transformer - Page 1 of 1

A058b0



| View Online at https://aerobasegroup.com/nsn/5950-00-681-2096 |
|--|
| Reliability Indicator: |
| Not established |
| Center To Center Distance Between Mounting Facilities Parallel To Length: |
| 4.375 inches single mounting facility single center group |
| Center To Center Distance Between Mounting Facilities Parallel To Width: |
| 3.625 inches single mounting facility single center group |
| Mounting Slot Width: |
| 0.313 inches single group and 0.375 inches single group |
| Frequency Rating: |
| 47.5 hertz single component and 63.0 hertz single component |
| nput-output Phase Relationship: |
| Single phase to single phase single component |
| Body Length: |
| 5.000 inches |
| Body Width: |
| 5.375 inches |
| Body Height: |
| 5.625 inches |
| nclosure Type: |
| Open |
| Mounting Facility Quantity: |
| 4 single group |
| Mounting Method: |
| Slot single group |
| Winding Function And Quantity: |
| 1 primary single component and 1 secondary single component |
| Winding Operating Current: |
| 35.0 amperes ac single component single secondary |
| Winding Operating Voltage: |
| 90.00 ac volts single component single primary and 95.00 ac volts single component single primary and 100.00 ac volts single component |
| single primary and 105.00 ac volts single component single primary and 110.00 ac volts single component single primary and 115.00 ac |
| volts single component single primary and 120.00 ac volts single component single primary |
| Terminal Type And Quantity: |
| 10 screw |
| Shelf Life: |
| N/a |
| Unit Of Measure: |
| - |
| Demilitarization: |
| No |
| Filg: |
| |