NSN 5985-00-134-9902

Fixed Attenuator - Page 1 of 2



-134-9902

| View Online at https://aerobasegroup.com/nsn/5985-0 |)0- |
|---|-----|
| Application Design: | |
| Transmission line | |
| Body Material: | |
| Brass, qq-b-626, comp 22, 1/2h | |
| Body Style: | |
| Round, terminal/terminals in opposite surface | |
| Body Surface Treatment: | |
| Silver plated, qq-s-365 | |
| Overall Length: | |
| 2.688 inches | |
| Overall Diameter: | |
| 0.813 inches | |
| Operating Tempurature Range: | |
| -55.0/+125.0 degrees celsius | |
| Voltage Standing Wave Ratio: | |
| 1.20 and 1.25 | |
| Input Impedance Rating In Ohms: | |
| 50.0 | |
| Output Impedance Rating In Ohms: | |
| 50.0 | |
| Coaxial Connector Series Designation: | |
| N | |
| Power Rating: | |
| 2.0 watts average and 300.0 watts peak | |
| Rf Signal Attenuation In Decibels: | |
| 6.0 | |
| Voltage Standing Wave Ratio Frequency Range: | |
| +0.0 to 3.0 gigahertz and +3.0/+6.0 gigahertz | |
| Attenuation Accuracy Reference Frequency: | |
| 6.0 gigahertz | |
| Attenuation Accuracy In Decibels: | |
| -0.50 to 0.50 | |
| Connection Type Per Function: | |
| Female output and male input | |
| Unpackaged Unit Weight: | |
| 2.400 ounces | |
| Mounting Method: | |
| Connector | |
| Terminal Type And Quantity: | |
| 2 connector | |
| Frequency Range: | |

Between 0.000 hertz and 6.000 gigahertz

NSN 5985-00-134-9902 Fixed Attenuator - Page 2 of 2



| Precious Material And Location: |
|---------------------------------|
| Body surface silver |
| Precious Material: |
| Silver |
| Shelf Life: |
| N/a |
| Unit Of Measure: |
| |
| Demilitarization: |
| No |

Fiig: A20000