Alternating Current Motor - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/6105-01-189-9936

| VIE | w Online at https://aerobasegroup.com/nsn/6105-01-189-9936 |
|-----|---|
| Ke | yway Width: |
| 0.5 | 00 inches single end |
| Ke | yway Depth: |
| 0.2 | 50 inches single end |
| Sh | aft Diameter: |
| 2.1 | 25 inches single end |
| Ke | yway Length: |
| 3.8 | 75 inches single end |
| Du | ty Cycle: |
| Co | ntinuous |
| Inc | losure Feature: |
| To | tally enclosed |
| Мо | ounting Method: |
| Fix | ed base |
| Мо | ounting Facility Type And Quantity: |
| 4 u | inthreaded hole |
| Co | oling Method: |
| Fa | n cooled |
| Cu | rrent Rating Method: |
| Loa | ad |
| Inc | losure Specificationification: |
| Ne | ma |
| Fra | ame Size Designation: |
| 320 | 6t |
| Ро | wer Rating: |
| 50. | 000 horsepower output |
| Le | ngth Of Shaft From Housing: |
| 5.2 | 50 inches single end |
| Sh | aft Center To Mounting Surface Distance: |
| 8.0 | 00 inches single end |
| Ce | nter To Center Distance Between Mounting Facilities Parallel To Length: |
| 12. | 000 inches |
| Te | mpurature Rating: |
| 40. | 0 ambient degrees celsius |
| Ro | tor Speed Rating In Rpm: |
| 17 | 50.0 single full load |
| Ce | nter To Center Distance Between Mounting Facilities Parallel To Width: |
| 12. | 500 inches |
| Cu | rrent Rating In Amps: |
| 110 | 6.000 first multiple input or 58.000 second multiple input |
| 6 | nnection Type And Voltage Rating In Volts: |

Connection Type And Voltage Rating In Volts:

208.0 line to neutral low input or 230.0 line to neutral high input or 460.0 line to neutral second multiple input

NSN 6105-01-189-9936

Alternating Current Motor - Page 2 of 2

Shaft End Characteristic:

A9 single style single end

Phase:

Three input

Frequency In Hertz:

60.0 input

Shelf Life:

N/a

Unit Of Measure:

Demilitarization:

No

Fiig:

A271a0

