NSN 5841-01-483-6710

Radar Set Control - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/5841-01-483-6710

| Maximum Voltage Rating In Volts: |
|---|
| 118.0 ac and 28.0 dc |
| End Application: |
| An/apy-3 |
| Inclosure Type: |
| Encased |
| Current Rating In Amps: |
| 2.7 |
| Power Source: |
| External |
| Maximum Wattage Rating In Watts: |
| 272.00 |
| Maximumlength: |
| 22.000 inches |
| Maximumwidth: |
| 16.280 inches |
| Maximumheight: |
| 7.650 inches |
| Criticality Code Justification: |
| Feat |
| Phase: |
| Three |
| Special Features: |
| E.S.D. Sensitive unit |
| Frequency In Hertz: |
| 400.0 |
| Functional Description: |
| Processor control and radar computer interface, also provides phase shifter control data to antenna |
| Shelf Life: |
| N/a |
| Unit Of Measure: |
| |
| Demilitarization: |
| Yes - demil/mli |
| Fiig: |
| A31700 |