NSN 5915-01-372-4818

Radio Frequency Interference Filter - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/5915-01-372-4818

Source Impedance Rating Per Function:

50.0 ohms 1st radio interference50.0 ohms 2nd radio interference

Load Impedance Per Function:

50.0 ohms 1st radio interference50.0 ohms 2nd radio interference

Power Line Frequency Rating Per Function In Hertz:

60.0 1st radio interference60.0 2nd radio interference

Operating Current Rating Per Function In Amps:

5.0 1st radio interference5.0 2nd radio interference

Principal Circuitry Type Per Function:

Inductance-capacitance-resistance 1st radio interference inductance-capacitance-resistance 2nd radio interference

Full Load Insertion Loss Frequencies In Megahertz:

 $20.0 \mbox{ and } 40.0 \mbox{ and } 65.0 \mbox{ and } 65.0 \mbox{ and } 65.0 \mbox{ and } 60.0$

Operating Voltage Rating And Type Per Function:

125.0 volts ac 1st radio interference 1st function and 250.0 volts ac 1st radio interference 1st function 125.0 volts ac 2nd radio interference

2nd function and 250.0 volts ac 2nd radio interference 2nd function

Body Material:

Metal

Body Surface Treatment:

Tin

Shelf Life:

N/a

Unit Of Measure:

Demilitarization:

No

Fiig:

A047b0