Extractor Post Fuseholder - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5920-00-538-6484

Body Material:	
Plastic	
Body Style:	
Bushing mounted type	
Overall Length:	
2.812 inches	
Bushing Diameter:	
0.625 inches	
Overall Diameter:	
0.812 inches	
Environmental Protection:	
Any acceptable	
Contact Material:	
Copper	
Contact Surface Treatment:	
Silver plated	
Interruption Indicator Method:	
Incandescent lamp	
Fuse Accommodation Quantity:	
1	
Accommodated Fuse Length:	
1.250 inches	
Accommodated Ferrule Diameter:	
0.250 inches	
Indicating Lamp Voltage Range In Volts:	
+22.0/+33.0	
Length From Front Protrusion To Mounting Surface:	
1.188 inches	
Bushing Thread Length:	
0.438 inches	
Bushing Hole Diameter:	
Between 0.625 inches and 0.635 inches	
Flatted Side Bushing Hole Length:	
Between 0.585 inches and 0.595 inches	
Current Carrying Rating In Amps:	
20.0	
Fuse Terminal Type Accommodated:	
Ferrule	
Voltage In Volts:	
250.0	
Terminal Type And Quantity:	
2 tab, solder lug	

NSN 5920-00-538-6484

Extractor Post Fuseholder - Page 2 of 2

AeroBase Group

Shelf Life:

N/a

Unit Of Measure:

Demilitarization:

No

Fiig:

A014a0