Extractor Post Fuseholder - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5920-00-615-7110

## **Body Material:**

Plastic, phenolic, mil-m-14, type cfg

**Body Style:** 

Bushing mounted type

## **Terminal Material:**

Brass

## **Terminal Surface Treatment:**

Electrotinned

#### **Overall Length:**

2.375 inches

#### **Bushing Diameter:**

0.625 inches

## Mounting Hole Quantity:

1

#### **Overall Diameter:**

0.938 inches

# **Environmental Protection:**

Any acceptable

#### Mounting Hole Style:

**Bushing mounting** 

## **Contact Material:**

Brass

## **Contact Surface Treatment:**

Tin plated

## Interruption Indicator Method:

Neon lamp

## **Fuse Accommodation Quantity:**

1

## Accommodated Fuse Length:

1.250 inches

## Accommodated Ferrule Diameter:

0.250 inches

#### **Resistor Rating:**

27.0 kilohms

# Indicating Lamp Voltage Range In Volts:

+100.0/+125.0

## Length From Front Protrusion To Mounting Surface:

0.812 inches

## **Bushing Thread Length:**

0.547 inches

## Cap Diameter:

0.938 inches

Extractor Post Fuseholder - Page 2 of 2



**Bushing Hole Diameter:** Between 0.627 inches and 0.635 inches Flatted Side Bushing Hole Length: Between 0.567 inches and 0.575 inches **Current Carrying Rating In Amps:** 20.0 Fuse Terminal Type Accommodated: Ferrule Voltage In Volts: 125.0 **Special Features:** Indicator light goes off when fuse blows **Terminal Type And Quantity:** 2 tab, solder lug Shelf Life: N/a Unit Of Measure: ---Demilitarization: No Fiig: A014a0