Extractor Post Fuseholder - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5920-00-705-2916

Body Style:

Bushing mounted type

Overall Length:

3.281 inches

Bushing Diameter:

0.625 inches

Mounting Hole Quantity:

1

Overall Diameter:

0.812 inches

Environmental Protection:

Any acceptable

Mounting Hole Style:

Bushing mounting

Contact Material:

Brass

Contact Surface Treatment:

Tin plated

Interruption Indicator Method:

Incandescent lamp

Fuse Accommodation Quantity:

1

Accommodated Fuse Length:

1.250 inches

Accommodated Ferrule Diameter:

0.250 inches

Resistor Rating:

15.0 ohms

Indicating Lamp Voltage Range In Volts:

+4.0/+6.0

Length From Front Protrusion To Mounting Surface:

1.187 inches

Bushing Thread Length:

1.656 inches

Cap Diameter:

0.812 inches

Bushing Hole Diameter:

0.630 inches

Flatted Side Bushing Hole Length:

0.590 inches

Current Carrying Rating In Amps:

20.0

NSN 5920-00-705-2916

Extractor Post Fuseholder - Page 2 of 2



Fuse Terminal Type Accommodated:

Ferrule

Voltage In Volts:

6.0

Terminal Type And Quantity:

2 tab, solder lug

Shelf Life:

N/a

Unit Of Measure:

Demilitarization:

No

Fiig:

A014a0