

View Online at <https://aerobasegroup.com/nsn/5935-01-653-1510>

Application Design:

Transmission line

Body Style:

Irregular

Overall Length:

6.9 inches

Center To Center Distance Between Mounting Facilities Parallel To Length:

3.63 inches

Overall Height:

1.0 inches

Overall Width:

2.0 inches

Unthreaded Mounting Hole Diameter:

0.120 inches

Coaxial Connector Series Designation:

Sma

Insertion Loss At Minimum Attenuation In Maximum Decibels:

0.6

Mounting Facility Type And Quantity:

4 unthreaded hole

Frequency Range:

8.0 gigahertz

Adjustment Device Type And Quantity:

1 knob

Impedance Rating In Ohms:

50.0 output

Product Name:

Adjustable phase trimmer

Special Features:

Is rectangular with the 2 coaxial connectors at one end and the adjusting knob at the other. The input power is 100.0 watts.

Terminal Type And Quantity:

2 connector, coaxial, female

Shelf Life:

N/a

Unit Of Measure:

--

Demilitarization:

No

Fiig:

A039b0