## NSN 5950-00-132-3489

Audio Frequency Transformer - Page 1 of 2



| View Online at https://aerobasegroup.com/nsn/5950-00-132-3489             |
|---|
| Reliability Indicator:  |
| Not established   |
| Center To Center Distance Between Mounting Facilities Parallel To Length: |
| 1.188 inches single mounting facility single center group                 |
| Center To Center Distance Between Mounting Facilities Parallel To Width:  |
| 1.188 inches single mounting facility single center group                 |
| Impedance Rating In Ohms:   |
| 12500.0 single component single secondary                                 |
| Frequency Rating:   |
| 100.0 hertz single component and 15.0 kilohertz single component          |
| Primary To Secondary Turn Ratio:  |
| 0.5 to 5 single component   |
| Winding Shielding Method:   |
| Internal shield brought out to terminal single component                  |
| Body Length:  |
| 2.313 inches  |
| Body Width:   |
| 1.563 inches  |
| Body Height:  |
| 1.563 inches  |
| Inclosure Type:   |
| Hermetically sealed   |
| Mounting Facility Quantity:   |
| 4 single group  |
| Mounting Method:  |
| Threaded stud single group  |
| Winding Function And Quantity:  |
| 2 primary single component and 1 secondary single component               |
| Thready Qty Per Inch (tpi):   |
| 32 single group   |
| Thread Size:  |
| 0.138 inches single group   |
| Thread Series Designator:   |
| Unc single group  |
| Terminal Type And Quantity:   |
| 7 wire hook   |
| Shelf Life:   |
| N/a   |
| Unit Of Measure:  |

Demilitarization:

No

## NSN 5950-00-132-3489

Audio Frequency Transformer - Page 2 of 2



Fiig:

A058b0