## NSN 5950-00-166-3360

Audio Frequency Transformer - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/5950-00-166-3360

Reliability Indicator:
Not established
Center To Center Distance Between Mounting Facilities Parallel To Length:
2.187 inches single mounting facility single center group
Center To Center Distance Between Mounting Facilities Parallel To Width:
2.000 inches single mounting facility single center group
Mounting Slot Width:
0.187 inches single group
Impedance Rating In Ohms:
8.0 single component single secondary and 16.0 single component single secondary and 250.0 single component single secondary
Frequency Rating:
200.0 hertz single component and 8.0 kilohertz single component
Maximum Transformer Power Rating:
20.0 watts single component
Body Length:
2.810 inches
Body Width:
2.500 inches
Body Height:
2.310 inches
Inclosure Type:
Fully enclosed
Mounting Facility Quantity:
4 single group
Mounting Method:
Flange single group and slot single group
Winding Function And Quantity:
1 primary single component and 1 secondary single component
Winding Operating Current:
200.0 milliamperes dc single component single primary
Terminal Type And Quantity:
7 tab, solder lug
Shelf Life:
N/a
Unit Of Measure:
<del></del>
Demilitarization:
No
Fiig:
A058b0