NSN 5950-00-179-0778

Radio Frequency Transformer - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-00-179-0778

Turn Quantity:

81-7/8 single component single secondary

Inductance Rating:

312.00 microhenries single component single secondary

Frequency Rating:

410.0 kilohertz single component and 850.0 kilohertz single component

Coil Form Type:

Hollow single component

Adjustment Device Drive Type:

Slotted screw single component

Body Length:

1.375 inches

Body Width:

1.125 inches

Body Height:

1.438 inches

Distance Between Mounting Facility Centers:

0.812 inches single mounting facility single center group

Inclosure Type:

Fully enclosed

Mounting Facility Quantity:

2 single group

Mounting Method:

Threaded hole single group

Winding Function And Quantity:

1 primary single component and 1 secondary single component

Thready Qty Per Inch (tpi):

40 single group

Thread Size:

0.112 inches single group

Winding Conductor Size:

0.00353 inches american wire gage single component single primary

Adjustment Method And Quantity:

1 adjustable core single component

Special Features:

Core iron material; coil form plastic material; case phenolic plastic material

Thread Series Designator:

Unc single group

Terminal Type And Quantity:

4 tab, solder lug

Shelf Life:

N/a

NSN 5950-00-179-0778

Radio Frequency Transformer - Page 2 of 2



| | | | ure: | |
|--|--|--|------|--|
| | | | | |
| | | | | |

--

Demilitarization:

No

Fiig:

A058b0