Audio Frequency Transformer - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/5950-00-223-4675

Poliability Indicator
Reliability Indicator:
Center To Center Distance Between Mounting Facilities Parallel To Length:
2.750 inches single mounting facility single center group
Center To Center Distance Between Mounting Facilities Parallel To Width:
2.750 inches single mounting facility single center group
Mounting Hole Diameter:
0.188 inches single group
Impedance Rating In Ohms:
1000.0 single component single primary
Frequency Rating:
60.0 hertz single component and 8.0 kilohertz single component
Maximum Transformer Power Rating:
10.0 watts single component
Primary To Secondary Turn Ratio:
1 to 1-6/10 single component
Body Length:
4.000 inches
Body Outside Diameter:
3.074 inches
Inclosure Type:
Hermetically sealed
Mounting Facility Quantity: 4 single group
Mounting Method:
Flange single group and unthreaded hole single group Winding Function And Quantity:
1 primary single component and 2 secondary single component
Winding Operating Current:
3.5 milliamperes dc single component single primary
Terminal Type And Quantity: 6 tab, solder lug
Shelf Life: N/a
Unit Of Measure:
Unit Of Measure:
 Demilitarization:
No
A058b0