NSN 5950-00-263-6586

Radio Frequency Coil - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-00-263-6586

Reliability Indicator:
Not established
Turn Quantity:
10 single component single winding
Inductance Rating:
1.19 microhenries single component single winding
Coil Form Type:
Hollow single component
Core Construction:
Powdered single component
Adjustment Device Drive Type:
Slotted screw single component
Body Length:
2.219 inches
Body Outside Diameter:
0.928 inches
Distance Between Mounting Facility Centers:
0.969 inches single mounting facility single center group
Inclosure Type:
Fully enclosed
Mounting Facility Quantity:
2 single group
Mounting Method:
Threaded stud single group
Rating Method:
Winding turns single component single winding
Winding turns single component single winding Thready Qty Per Inch (tpi):
Thready Qty Per Inch (tpi):
Thready Qty Per Inch (tpi): 40 single group
Thready Qty Per Inch (tpi): 40 single group Thread Size:
Thready Qty Per Inch (tpi): 40 single group Thread Size: 0.112 inches single group
Thready Qty Per Inch (tpi): 40 single group Thread Size: 0.112 inches single group Winding Conductor Size:
Thready Qty Per Inch (tpi): 40 single group Thread Size: 0.112 inches single group Winding Conductor Size: 0.00795 inches american wire gage single component single winding
Thready Qty Per Inch (tpi): 40 single group Thread Size: 0.112 inches single group Winding Conductor Size: 0.00795 inches american wire gage single component single winding Adjustment Method And Quantity:
Thready Qty Per Inch (tpi): 40 single group Thread Size: 0.112 inches single group Winding Conductor Size: 0.00795 inches american wire gage single component single winding Adjustment Method And Quantity: 1 adjustable core single component
Thready Qty Per Inch (tpi): 40 single group Thread Size: 0.112 inches single group Winding Conductor Size: 0.00795 inches american wire gage single component single winding Adjustment Method And Quantity: 1 adjustable core single component Thread Series Designator:
Thready Qty Per Inch (tpi): 40 single group Thread Size: 0.112 inches single group Winding Conductor Size: 0.00795 inches american wire gage single component single winding Adjustment Method And Quantity: 1 adjustable core single component Thread Series Designator: Unc single group
Thready Qty Per Inch (tpi): 40 single group Thread Size: 0.112 inches single group Winding Conductor Size: 0.00795 inches american wire gage single component single winding Adjustment Method And Quantity: 1 adjustable core single component Thread Series Designator: Unc single group Terminal Type And Quantity:
Thready Qty Per Inch (tpi): 40 single group Thread Size: 0.112 inches single group Winding Conductor Size: 0.00795 inches american wire gage single component single winding Adjustment Method And Quantity: 1 adjustable core single component Thread Series Designator: Unc single group Terminal Type And Quantity: 2 solder stud

--

NSN 5950-00-263-6586

Radio Frequency Coil - Page 2 of 2



Demilitarization:

No

Fiig:

A058b0