NSN 5950-00-538-6887

Audio Frequency Transformer - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/5950-00-538-6887

D	ام	ia	h	ii	i٤٠	, 1	ın	ч	i	са	4	_	r	
к	еı	ıα	D	Ш	IU	7 I	Ш	u	ı	Ca	τ	U	Г	

Not established

Center To Center Distance Between Mounting Facilities Parallel To Length:

1.312 inches single mounting facility single center group

Center To Center Distance Between Mounting Facilities Parallel To Width:

1.312 inches single mounting facility single center group

Impedance Rating In Ohms:

50.0 and 150.0 single component all secondary

Frequency Rating:

50.0 hertz and 20.0 kilohertz single component

Maximum Transformer Power Rating:

23.0 decibels single component

Primary To Secondary Turn Ratio:

1 to 1 to 25 single component

Body Length:

2.250 inches

Body Outside Diameter:

1.500 inches

Inclosure Type:

Hermetically sealed

Mounting Method:

Flange and unthreaded hole single group

Winding Function And Quantity:

1 primary and 2 secondary single component

Winding Operating Current:

8.0 milliamperes dc single component single primary

Terminal Type And Quantity:

8 tab, solder lug

o tab, colaci la

Shelf Life: N/a

Unit Of Measure:

--

Demilitarization:

No

Fiig:

A058b0