NSN 5950-00-586-6942

Radio Frequency Coil - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-00-586-6942

Reliability Indicator:
Not established
Turn Quantity:
8-1/4 single component single winding
Inductance Rating:
0.44 microhenries single component single winding and 0.76 microhenries single component single winding
Coil Form Type:
Hollow single component
Core Construction:
Powdered single component
Adjustment Device Drive Type:
Slotted screw single component
Body Length:
0.875 inches
Body Outside Diameter:
0.250 inches
Inclosure Type:
Fully enclosed
Mounting Method:
Threaded bushing single group
Rating Method:
Winding turns single component single winding and electrical single component single winding
Thread Size:
0.190 inches single group
Winding Conductor Size:
0.02010 inches american wire gage single component single winding
Winding Operating Current:
1.6 amperes dc single component single winding
Dc Resistance Rating In Ohms:
0.030 single component single winding
Quality Factor:
52 single component single winding and 80 single component single winding
Adjustment Method And Quantity:
1 adjustable core single component
Thread Series Designator:
Unf single group
Terminal Type And Quantity:
2 tab, solder lug
Shelf Life:
N/a
Unit Of Measure:

--

NSN 5950-00-586-6942

Radio Frequency Coil - Page 2 of 2



Demilitarization:

No

Fiig:

A058b0