## NSN 5950-00-645-1919

Audio Frequency Transformer - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-00-645-1919

### **Reliability Indicator:**

Not established

#### Center To Center Distance Between Mounting Facilities Parallel To Length:

2.438 inches single mounting facility single center group

### Center To Center Distance Between Mounting Facilities Parallel To Width:

2.188 inches single mounting facility single center group

### Impedance Rating In Ohms:

6000.0 single component single primary

#### Frequency Rating:

300.0 hertz single component and 15.0 kilohertz single component

#### **Maximum Transformer Power Rating:**

20.0 watts single component

### **Primary To Secondary Turn Ratio:**

1 to 1 to 1-4/10 single component

#### **Body Length:**

3.250 inches

#### **Body Width:**

3.000 inches

### **Body Height:**

3.719 inches

### Inclosure Type:

Hermetically sealed

### **Mounting Facility Quantity:**

4 single group

### **Mounting Method:**

Threaded hole single group

### **Winding Function And Quantity:**

1 primary single component and 2 secondary single component

### Thready Qty Per Inch (tpi):

32 single group

### **Thread Size:**

0.190 inches single group

### **Winding Operating Current:**

70.0 milliamperes dc single component single primary

#### **Thread Series Designator:**

Unf single group

### **Terminal Type And Quantity:**

8 tab, solder lug

### Shelf Life:

N/a

### **Unit Of Measure:**

--

# NSN 5950-00-645-1919

Audio Frequency Transformer - Page 2 of 2



Demilitarization:

No

Fiig:

A058b0