## NSN 5950-00-646-5273

Power Autotransformer Transformer - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/5950-00-646-5273 **Reliability Indicator:** Not established Frequency Rating: 400.0 hertz single component Input-output Phase Relationship: Single phase to single phase single component **Body Length:** 1.187 inches **Body Width:** 1.125 inches **Body Height:** 3.562 inches **Inclosure Type:** Hermetically sealed **Mounting Method:** Terminal single group **Winding Function And Quantity:** 1 primary, fixed autotransformer type single component Winding Operating Voltage: 3.00 ac volts single component single primary output and 3.60 ac volts single component single primary output and 4.20 ac volts single component single primary output and 4.80 ac volts single component single primary output and 5.40 ac volts single component single primary output and 6.00 ac volts single component single primary output and 6.60 ac volts single component single primary output and 7.80 ac volts single component single primary output and 8.40 ac volts single component single primary output and 9.00 ac volts single component single primary output and 9.60 ac volts single component single primary output and 10.20 ac volts single component single primary output and 10.80 ac volts single component single primary output and 11.40 ac volts single component single primary output and 12.00 ac volts single component single primary output and 12.60 ac volts single component single primary output and 13.20 ac volts single component single primary output and 13.80 ac volts single component single primary output and 14.40 ac volts single component single primary output **Terminal Type And Quantity:** 22 wire lead Shelf Life:

N/a

**Unit Of Measure:** 

**Demilitarization:** 

No

Fiig:

A058b0