## NSN 5950-00-648-2222

Audio Frequency Transformer - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-00-648-2222
Reliability Indicator:
Not established
Center To Center Distance Between Mounting Facilities Parallel To Length:
3.375 inches single mounting facility single center group
Center To Center Distance Between Mounting Facilities Parallel To Width:
4.000 inches single mounting facility single center group
Transformer Function:
Modulation
Impedance Rating In Ohms:
8000.0 single component single primary
Frequency Rating:
200.0 hertz single component and 20.0 kilohertz single component
Maximum Transformer Power Rating:
120.0 watts single component
Body Length:
5.125 inches
Body Width:
4.500 inches
Body Height:
7.500 inches
Inclosure Type:
Hermetically sealed
Mounting Facility Quantity:
4 single group
Mounting Method:
Threaded stud single group
Winding Function And Quantity:
1 primary single component and 2 secondary single component
Thready Qty Per Inch (tpi):
20 single group
Thread Size:
0.250 inches single group
Winding Operating Current:
300.0 milliamperes dc single component 1st secondary
Thread Series Designator:
Unc single group
Terminal Type And Quantity:
8 standoff, solder lug
Shelf Life:
N/a
Unit Of Measure:

--

## NSN 5950-00-648-2222

Audio Frequency Transformer - Page 2 of 2



_		••	• •				
וו	em	ш	112	rız	211	n	٠.

No

Fiig:

A058b0