## NSN 5950-00-648-6620

Audio Frequency Transformer - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-00-648-6620

### **Reliability Indicator:**

Not established

### Center To Center Distance Between Mounting Facilities Parallel To Length:

1.688 inches single mounting facility single center group

### Center To Center Distance Between Mounting Facilities Parallel To Width:

1.438 inches single mounting facility single center group

### **Overall Height:**

3.520 inches

### Impedance Rating In Ohms:

10000.0 single component single primary

#### Frequency Rating:

1.35 kilohertz single component and 1.65 kilohertz single component

#### **Maximum Transformer Power Rating:**

500.0 milliwatts single component

#### **Primary To Secondary Turn Ratio:**

1 to 1-7/16 to 1-7/16 single component

#### **Winding Shielding Method:**

Internal shield grounded to inclosure and core single component

### **Body Length:**

2.312 inches

### **Body Width:**

2.062 inches

### **Body Height:**

3.125 inches

#### **Inclosure Type:**

Hermetically sealed

### **Mounting Facility Quantity:**

4 single group

#### **Mounting Method:**

Threaded stud single group

### **Winding Function And Quantity:**

1 primary single component and 2 secondary single component

### Thready Qty Per Inch (tpi):

32 single group

### Thread Size:

0.138 inches single group

### **Winding Operating Current:**

6.0 milliamperes dc single component single primary

### **Thread Series Designator:**

Unc single group

### **Terminal Type And Quantity:**

6 tab, solder lug

# NSN 5950-00-648-6620

Audio Frequency Transformer - Page 2 of 2



		fe:

N/a

**Unit Of Measure:** 

--

Demilitarization:

No

Fiig:

A058b0