## NSN 5950-00-679-2818

Audio Frequency Transformer - Page 1 of 2



| View Online at https://aerobasegroup.com/nsn/5950-00-679-2818             |
|---|
| Reliability Indicator:  |
| Not established   |
| Center To Center Distance Between Mounting Facilities Parallel To Length: |
| 1.375 inches single mounting facility single center group                 |
| Center To Center Distance Between Mounting Facilities Parallel To Width:  |
| 1.250 inches single mounting facility single center group                 |
| Impedance Rating In Ohms:   |
| 10000.0 single component single primary                                   |
| Frequency Rating:   |
| 900.0 hertz single component and 1.1 kilohertz single component           |
| Maximum Transformer Power Rating:   |
| 2.5 watts single component  |
| Primary To Secondary Turn Ratio:  |
| 1 to 1600 single component  |
| Body Length:  |
| 1.938 inches  |
| Body Width:   |
| 1.812 inches  |
| Body Height:  |
| 2.438 inches  |
| Inclosure Type:   |
| Fully enclosed  |
| Mounting Facility Quantity:   |
| 4 single group  |
| Mounting Method:  |
| Threaded stud single group  |
| Winding Function And Quantity:  |
| 1 primary single component and 1 secondary single component               |
| Thready Qty Per Inch (tpi):   |
| 32 single group   |
| Thread Size:  |
| 0.138 inches single group   |
| Winding Operating Current:  |
| 30.0 milliamperes dc single component single primary                      |
| Thread Series Designator:   |
| Unc single group  |
| Terminal Type And Quantity:   |
| 5 solder stud   |
| Shelf Life:   |

--

N/a

**Unit Of Measure:** 

## NSN 5950-00-679-2818

Audio Frequency Transformer - Page 2 of 2



Demilitarization:

No

Fiig:

A058b0