NSN 5950-00-710-1935

Radio Frequency Coil - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-00-710-1935

| Reliability Indicator: |
|--|
| Not established |
| Turn Quantity: |
| 7-1/4 single component single winding |
| Mounting Hole Diameter: |
| 0.125 inches single group |
| Inductance Rating: |
| 0.725 microhenries single component single winding |
| Coil Form Type: |
| Hollow single component |
| Core Construction: |
| Powdered single component |
| Adjustment Device Drive Type: |
| Slotted screw single component |
| Body Length: |
| 1.375 inches |
| Body Outside Diameter: |
| 0.500 inches |
| Distance Between Mounting Facility Centers: |
| 0.875 inches single mounting facility single center group |
| Inclosure Type: |
| Open |
| Mounting Facility Quantity: |
| 2 single group |
| Mounting Method: |
| Flange single group and unthreaded hole single group |
| Rating Method: |
| Electrical single component single winding and winding turns single component single winding |
| Winding Conductor Size: |
| 0.03196 inches american wire gage single component single winding |
| Quality Factor: |
| 147 single component single winding |
| Adjustment Method And Quantity: |
| 1 adjustable core single component |
| Terminal Type And Quantity: |
| 2 tab, solder lug |
| Shelf Life: |
| N/a |
| Unit Of Measure: |
| |
| Demilitarization: |
| No |

NSN 5950-00-710-1935

Radio Frequency Coil - Page 2 of 2



Fiig:

A058b0