## NSN 5950-00-816-3333

Radio Frequency Coil - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-00-816-3333

| Reliability Indicator:   |
|--|
| Not established  |
|  |
| Overall Length: 0.844 inches   |
| Turn Quantity:   |
| 22-1/2 single component single winding   |
| Inductance Rating:   |
| 3.01 microhenries single component single winding  |
| Coil Form Type:  |
| Hollow single component  |
| Core Construction:   |
| Powdered single component  |
| Adjustment Device Drive Type:  |
| Slotted screw single component   |
| Overall Diameter:  |
| 0.260 inches   |
| Inclosure Type:  |
| Fully enclosed   |
| Mounting Method:   |
| Threaded bushing single group  |
| Rating Method:   |
| Electrical single component single winding and winding turns single component single winding |
| Thready Qty Per Inch (tpi):  |
| 32 single group  |
| Thread Size:   |
| 0.190 inches single group  |
| Winding Conductor Size:  |
| 0.01003 inches american wire gage single component single winding                            |
| Winding Operating Current:   |
| 200.0 microamperes dc single component single winding  |
| Dc Resistance Rating In Ohms:  |
| 0.179 single component single winding  |
| Adjustment Method And Quantity:  |
| 1 adjustable core single component   |
| Thread Series Designator:  |
| Unf single group   |
| Terminal Type And Quantity:  |
| 2 tab, solder lug  |
| Shelf Life:  |
| N/a  |
| Unit Of Measure:   |
|  |

--

## NSN 5950-00-816-3333

Radio Frequency Coil - Page 2 of 2



Demilitarization:

No

Fiig:

A058b0