# NSN 5950-00-838-1934

Power Transformer - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-00-838-1934

# Reliability Indicator:

Not established

# Center To Center Distance Between Mounting Facilities Parallel To Length:

2.735 inches single mounting facility single center group and 2.765 inches single mounting facility single center group

# Center To Center Distance Between Mounting Facilities Parallel To Width:

2.172 inches single mounting facility single center group and 2.202 inches single mounting facility single center group

# Mounting Slot Width:

0.125 inches single group

#### **Frequency Rating:**

60.0 hertz single component

#### Input-output Phase Relationship:

Single phase to single phase single component

#### Maximum Transformer Power Rating:

160.0 volt-ampere single component

#### Body Length:

# 4.150 inches

Body Width:

3.000 inches

Body Height:

3.490 inches

#### Maximum Operating Temp:

105.0 degrees celsius

#### Inclosure Type:

Open

#### Mounting Facility Quantity:

4 single group

#### Mounting Method:

Bracket single group and slot single group

# Winding Function And Quantity:

1 primary single component and 2 secondary single component

#### Winding Operating Current:

26.7 milliamperes ac single component 2nd secondary

#### Winding Power Rating:

80.0 volts-amperes single component 1st secondary

#### Winding Operating Voltage:

560.00 ac volts single component all secondary

# Terminal Type And Quantity:

8 tab, solder lug

Shelf Life:

N/a

#### Unit Of Measure:

--

# NSN 5950-00-838-1934

Power Transformer - Page 2 of 2

Demilitarization:

No

Fiig:

A058b0

