## NSN 5950-00-965-9761

Radio Frequency Coil - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/5950-00-965-9761

| Turn Quantity:  |
|---|
| 7 single component single winding   |
| Inductance Rating:  |
| 0.41 microhenries single component single winding   |
| Coil Form Type:   |
| Hollow single component   |
| Core Construction:  |
| Powdered single component   |
| Adjustment Device Drive Type:   |
| Slotted screw single component  |
| Body Length:  |
| 1.562 inches  |
| Body Outside Diameter:  |
| 0.250 inches  |
| Inclosure Type:   |
| Open  |
| Mounting Method:  |
| Threaded bushing single group   |
| Thready Qty Per Inch (tpi):   |
| 32 single group   |
| Thread Size:  |
| 0.1875 inches single group  |
| Winding Conductor Size:   |
| 0.02846 inches american wire gage single component single winding   |
| Adjustment Method And Quantity:   |
| 1 adjustable core single component  |
| Special Features:   |
| Bushing 0.406 in. Lg; coil form ceramic material; color coded red-gray conductor w/enamel insulation; single layer wound type |
| Thread Series Designator:   |
| Uns single group  |
| Terminal Type And Quantity:   |
| 2 tab, solder lug   |
| Shelf Life:   |
| N/a   |
| Unit Of Measure:  |
|   |
| Demilitarization:   |
| No  |
|   |

Fiig:

A058b0