NSN 5950-00-972-6500

Power Transformer - Page 1 of 1



view Online at https://aerobasegroup.com/hsh/babo-ou-a/2-6500
Reliability Indicator:
Not established
Center To Center Distance Between Mounting Facilities Parallel To Length:
5.630 inches single mounting facility single center group
Center To Center Distance Between Mounting Facilities Parallel To Width:
8.130 inches single mounting facility single center group
Mounting Slot Width:
0.380 inches single group
Frequency Rating:
60.0 hertz single component
Input-output Phase Relationship:
Single phase to three phase single component
Maximum Transformer Power Rating:
1.0 kilovolt-ampere single component
Body Length:
17.875 inches
Body Width:
9.000 inches
Body Height:
6.440 inches
Inclosure Type:
Fully enclosed
Mounting Facility Quantity:
4 single group
Mounting Method:
Flange single group and slot single group
Winding Function And Quantity:
1 primary single component and 1 secondary single component
Winding Operating Current:
8.46 amperes ac single component single secondary
Winding Operating Voltage:
200.00 ac volts single component single primary and 220.00 ac volts single component single primary
Terminal Type And Quantity:
6 wire lead
Shelf Life:
N/a
Unit Of Measure:
Demilitarization:
No
Fiig:

A058b0