## NSN 5950-00-987-8826

Radio Frequency Coil - Page 1 of 2

2 tab, solder lug



View Online at https://aerobasegroup.com/nsn/5950-00-987-8826

Reliability Indicator:
Not established
Overall Length:
0.844 inches
Turn Quantity:
112 single component single winding
Overall Height:
0.531 inches
Overall Width:
0.578 inches
Inductance Rating:
260.00 microhenries single component single winding
Coil Form Type:
Hollow single component
Core Construction:
Powdered single component
Adjustment Device Drive Type:
Slotted screw single component
Body Length:
0.609 inches
Body Width:
0.578 inches
Body Height:
0.531 inches
Maximum Operating Temp:
85.0 degrees celsius
Mounting Tab Width:
0.050 inches
Inclosure Type:
Fully enclosed
Mounting Method:
Tab single group
Rating Method:
Electrical single component single winding and winding turns single component single winding
Winding Conductor Size:
0.00500 inches american wire gage single component single winding
Quality Factor:
100 single component single winding
Adjustment Method And Quantity:
1 adjustable core single component
Terminal Type And Quantity:

## NSN 5950-00-987-8826

Radio Frequency Coil - Page 2 of 2



_					
•	n	<b>0</b> 1	•	12	e:

N/a

**Unit Of Measure:** 

--

Demilitarization:

No

Fiig:

A058b0