NSN 5950-01-065-4290

Radio Frequency Transformer - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-01-065-4290

View Online at https://aerobasegroup.com/nsn/5950-01-065-4290
Reliability Indicator:
Not established
Turn Quantity:
12 single component single primary
Inductance Rating:
0.62 henry single component single primary and 1.04 henry single component single primary
Frequency Rating:
7.9 megahertz single component and 25.0 megahertz single component
Coil Form Type:
Hollow single component
Adjustment Device Drive Type:
Slotted screw single component
Body Length:
0.625 inches
Body Outside Diameter:
0.344 inches
Maximum Operating Temp:
71.0 degrees celsius
Inclosure Type:
Fully enclosed
Mounting Method:
Threaded bushing single group
Rating Method:
Electrical single component single primary and winding turns single component single primary
Winding Function And Quantity:
1 primary single component
Thready Qty Per Inch (tpi):
32 single group
Thread Size:
0.164 inches single group
Winding Conductor Size:
0.01420 inches american wire gage single component single primary
Adjustment Method And Quantity:
1 adjustable core single component
Thread Series Designator:
Unc single group
Terminal Type And Quantity:
3 tab, solder lug
Shelf Life:
N/a
Unit Of Measure:

-

NSN 5950-01-065-4290

Radio Frequency Transformer - Page 2 of 2



Demilitarization:

No

Fiig:

A058b0