## NSN 5950-01-093-8576

Radio Frequency Coil - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-01-093-8576

Reliability Indicator:					
Not established					
Turn Quantity:					
26-1/4 single component single winding					
Mounting Hole Diameter:					
0.060 inches single group					
Inductance Rating:					
4.23 microhenries single component single winding and 5.17 microhenries single component single winding					
Coil Form Type:					
Hollow single component					
Core Construction:					
Powdered single component					
Adjustment Device Drive Type:					
Slotted screw single component					
Body Length:					
0.400 inches					
Body Width:					
0.400 inches					
Body Height:					
0.480 inches					
Distance Between Mounting Facility Centers:					
0.200 inches single mounting facility single center group					
Inclosure Type:					
Fully enclosed					
Mounting Facility Quantity:					
2 single group					
Mounting Method:					
Unthreaded hole single group					
Rating Method:					
Winding turns single component single winding and electrical single component single winding					
Winding Conductor Size:					
0.00500 inches american wire gage single component single winding					
Winding Operating Current:					
520.0 milliamperes dc single component single winding					
Dc Resistance Rating In Ohms:					
0.880 single component single winding					
Quality Factor:					
50 single component single winding					
Adjustment Method And Quantity:					
1 adjustable core single component					
Terminal Type And Quantity:					

2 pin

## NSN 5950-01-093-8576

Radio Frequency Coil - Page 2 of 2



_				
c	hο	.1+		ife:
J	116		_	HG.

N/a

**Unit Of Measure:** 

--

Demilitarization:

No

Fiig:

A058b0