Power Autotransformer Transformer - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/5950-01-198-1825

# **Reliability Indicator:**

Not established

# Center To Center Distance Between Mounting Facilities Parallel To Length:

2.224 inches single mounting facility single center group and 2.286 inches single mounting facility single center group

# Center To Center Distance Between Mounting Facilities Parallel To Width:

2.040 inches single mounting facility single center group and 2.060 inches single mounting facility single center group

# Mounting Hole Diameter:

0.180 inches single group

#### **Frequency Rating:**

400.0 hertz single component

### Input-output Phase Relationship:

Single phase to single phase single component

### **Body Length:**

Between 2.690 inches and 2.750 inches

#### **Body Width:**

Between 2.550 inches and 2.750 inches

#### **Body Height:**

2.880 inches

#### Inclosure Type:

Fully enclosed

# **Mounting Facility Quantity:**

4 single group

# Mounting Method:

Unthreaded hole single group

### Winding Function And Quantity:

1 primary, fixed autotransformer type single component

### Winding Operating Current:

10.0 amperes ac single component single primary output

### Winding Operating Voltage:

12.50 ac volts single component single primary output and 16.00 ac volts single component single primary output and 30.00 ac volts single component single primary output

### **Terminal Type And Quantity:**

5 threaded stud

#### Shelf Life:

N/a

# Unit Of Measure:

---

# Demilitarization:

No

Fiig:

A058b0