## NSN 5950-01-259-5521

Power Transformer - Page 1 of 2

Reliability Indicator:



View Online at https://aerobasegroup.com/nsn/5950-01-259-5521

Not established
Overall Length:
3.375 inches
Center To Center Distance Between Mounting Facilities Parallel To Length:
2.812 inches single mounting facility single center group
Center To Center Distance Between Mounting Facilities Parallel To Width:
2.375 inches single mounting facility single center group
Overall Height:
2.875 inches
Overall Width:
3.375 inches
Mounting Slot Width:
0.203 inches single group
Frequency Rating:
50.0 hertz single component or 60.0 hertz single component
Input-output Phase Relationship:
Single phase to single phase single component
Maximum Transformer Power Rating:
100.0 volt-ampere single component
Inclosure Type:
Partially enclosed, double shell
Mounting Facility Quantity:
4 single group
Mounting Method:
Bracket single group and slot single group
Winding Function And Quantity:
2 primary single component and 1 secondary single component
Winding Operating Current:
434.8 milliamperes ac single component all primary
Winding Operating Voltage:
230.00 ac volts single component all primary
Special Features:
Secondary, jumper instead of fuse clip
Terminal Type And Quantity:
6 tab w/screw
Shelf Life:
N/a
Unit Of Measure:
Demilitarization:

No

## NSN 5950-01-259-5521

Power Transformer - Page 2 of 2



Fiig:

A058b0