## NSN 5950-01-387-4890

Radio Frequency Coil - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5950-01-387-4890

| Deliability Indicator   |
|---|
| Reliability Indicator:  |
| Not established   |
| Turn Quantity:  |
| 6-1/2 single component single winding   |
| Inductance Rating:  |
| 0.19 microhenries single component single winding and 0.31 microhenries single component single winding                             |
| Coil Form Type:   |
| Hollow single component   |
| Core Construction:  |
| Powdered single component   |
| Adjustment Device Drive Type:   |
| Shaft single component  |
| Body Length:  |
| Between 0.310 inches and 0.315 inches   |
| Body Width:   |
| Between 0.310 inches and 0.315 inches   |
| Body Height:  |
| Between 0.365 inches and 0.375 inches   |
| Mounting Tab Width:   |
| Between 0.045 inches and 0.050 inches   |
| Inclosure Type:   |
| Fully enclosed  |
| Mounting Method:  |
| Tab single group  |
| Rating Method:  |
| Electrical single component single winding and winding turns single component single winding  |
| Winding Conductor Size:   |
| 0.01264 inches american wire gage single component single winding   |
| Quality Factor:   |
| 90 single component single winding  |
| Adjustment Method And Quantity:   |
| 1 adjustable core single component  |
| Test Data Document:   |
| 80063-a3148301 drawing (this is the basic governing drawing, such as a contractor drawing, original equipment manufacturer drawing, |
| etc.; excludes any specification, standard or other document that may be referenced in a basic governing drawing)                   |
| Terminal Type And Quantity:   |
| 2 pin   |
| Shelf Life:   |
| N/a   |
| Unit Of Measure:  |
| <del></del>   |
| Demilitarization:   |

No

## NSN 5950-01-387-4890

Radio Frequency Coil - Page 2 of 2



Fiig:

A058b0