# NSN 5985-00-270-1096

Waveguide Adapter - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5985-00-270-1096

# Cross Sectional Shape:

Internal, rectangular external, rectangular

## Tubing Wall Construction Style:

Seamless single tubing segment

# Flange Quantity:

1

## Flange Inside Width:

1.503 inches single flange and 1.506 inches single flange

## Flange Inside Height:

0.753 inches single flange and 0.756 inches single flange

## Flange Outside Diameter:

3.110 inches single flange and 3.140 inches single flange

## Flange Depth:

0.360 inches single flange and 0.390 inches single flange

## Flange Connecting Hole Diameter:

0.199 inches single flange all connection facilities and 0.203 inches single flange all connection facilities

# Voltage Standing Wave Ratio:

1.25

**Coaxial Connector Series Designation:** 

Ν

Connector End Design:

Female

Adapter Length:

Between 1.855 inches and 1.885 inches

## Waveguide Outside Width:

Between 1.496 inches and 1.504 inches

## Waveguide Inside Width:

Between 1.368 inches and 1.376 inches

## Waveguide Inside Height:

Between 0.618 inches and 0.626 inches

## Waveguide Outside Height:

Between 0.746 inches and 0.754 inches

# Flange Connecting Facility And Quantity:

6 unthreaded hole single flange all connection facilities

## Adapter Diameter:

Between 3.110 inches and 3.140 inches

## Flange Style:

Cover type single flange

## Adapterheight:

Between 3.110 inches and 3.140 inches

## Material:

Copper alloy single tubing segment and flange

# NSN 5985-00-270-1096

Waveguide Adapter - Page 2 of 2



**Precious Material And Location:** 

Internal surfaces silver

**Precious Material:** 

Silver

Surface Treatment:

Silver single tubing segment and flange inside surfaces

Style Designator:

Waveguide to coaxial

Fsc Application Data:

Antennas, waveguides, and related equipment

Shelf Life:

N/a

Unit Of Measure:

---

#### Demilitarization:

Yes - demil/mli

#### Fiig:

A073a0