NSN 5985-00-484-9474

Waveguide Assembly - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5985-00-484-9474

Cross Sectional Shape:

Internal, rectangular external, rectangular

Flange Quantity:

6

Flange Inside Width:

0.705 inches third flange and 0.707 inches third flange

Flange Inside Height:

0.394 inches second flange and 0.396 inches second flange

Flange Outside Width:

1.298 inches fourth flange and 1.328 inches fourth flange

Flange Outside Height:

1.298 inches first flange and 1.328 inches first flange

Flange Depth:

0.298 inches third flange and 0.328 inches third flange

Flange Connecting Hole Diameter:

0.144 inches third flange all connection facilities and 0.147 inches third flange all connection facilities

Voltage Standing Wave Ratio:

1.15

Insertion Loss In Decibels:

0.30

Waveguide Outside Width:

Between 0.699 inches and 0.705 inches

Waveguide Inside Width:

Between 0.620 inches and 0.625 inches

Waveguide Inside Height:

Between 0.309 inches and 0.314 inches

Waveguide Outside Height:

Between 0.388 inches and 0.394 inches

Flange Connecting Facility And Quantity:

4 unthreaded hole all flanges all connection facilities

Flange Style:

Cover type third flange

Material:

Copper alloy all tubing segment and flange

Fsc Application Data:

Antennas, waveguides, and related equipment

Shelf Life:

N/a

Unit Of Measure:

--

Demilitarization:

Yes - demil/mli

NSN 5985-00-484-9474 Waveguide Assembly - Page 2 of 2



Fiig:

A073a0