NSN 5985-00-804-7896

Waveguide Adapter - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5985-00-804-7896

Unable To Decode:

Internal, rectangular external, rectangular

Tubing Wall Construction Style:

Seamless single tubing segment

Flange Quantity:

1

Flange Inside Width:

1.003 inches single flange and 1.006 inches single flange

Flange Inside Height:

0.503 inches single flange and 0.506 inches single flange

Flange Outside Width:

1.610 inches single flange and 1.640 inches single flange

Flange Outside Height:

1.610 inches single flange and 1.640 inches single flange

Flange Depth:

0.423 inches single flange and 0.453 inches single flange

Flange Connecting Hole Diameter:

0.169 inches single flange all connection facilities and 0.172 inches single flange all connection facilities

Voltage Standing Wave Ratio:

1.30

Adapter Length:

1.647 inches

Waveguide Outside Width:

Between 0.996 inches and 1.004 inches

Waveguide Inside Width:

Between 0.896 inches and 0.904 inches

Waveguide Inside Height:

Between 0.396 inches and 0.404 inches

Waveguide Outside Height:

Between 0.496 inches and 0.504 inches

Flange Connecting Facility And Quantity:

4 unthreaded hole single flange all connection facilities

Flange Style:

Cover type single flange

Adapterheight:

2.068 inches

Adapterwidth:

1.625 inches

Material:

Copper alloy single tubing segment and flange

Precious Material And Location:

Internal surfaces rhodium and internal surfaces silver

NSN 5985-00-804-7896

Waveguide Adapter - Page 2 of 2



Precious Material:

Rhodium and silver

Surface Treatment:

Copper all tubing segment and flange inside surfaces and rhodium all tubing segment and flange inside surfaces and silver all tubing

segment and flange inside surfaces

Style Designator:

Waveguide to coaxial

Fsc Application Data:

Antennas, waveguides, and related equipment

Shelf Life:

N/a

Unit Of Measure:

Demilitarization:

Yes - demil/mli

Fiig:

A073a0