## NSN 5985-00-906-3287

Waveguide Adapter - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5985-00-906-3287

## **Unable To Decode:**

Internal, rectangular external, rectangular

## **Tubing Wall Construction Style:**

Seamless single tubing segment

Flange Quantity:

1

## Flange Inside Width:

2.002 inches single flange

## Flange Inside Height:

1.002 inches single flange

## Flange Outside Diameter:

3.610 inches single flange and 3.640 inches single flange

#### Flange Depth:

0.360 inches single flange and 0.390 inches single flange

## Flange Connecting Hole Diameter:

0.199 inches single flange single connection facility

## **Voltage Standing Wave Ratio:**

1.25

## **Coaxial Connector Series Designation:**

N

## **Connector End Design:**

Female

## Adapter Length:

Between 1.985 inches and 2.015 inches

## **Waveguide Outside Width:**

Between 1.995 inches and 2.005 inches

## Waveguide Inside Width:

Between 1.867 inches and 1.877 inches

## **Waveguide Inside Height:**

Between 0.867 inches and 0.877 inches

## **Waveguide Outside Height:**

Between 0.995 inches and 1.005 inches

## Flange Connecting Facility And Quantity:

8 unthreaded hole single flange single connection facility

## **Adapter Diameter:**

Between 3.610 inches and 3.640 inches

## Flange Style:

Cover type single flange

## Adapterheight:

Between 3.297 inches and 3.327 inches

## **Special Features:**

Frequency range 3.95 to 5.85 ghz

# NSN 5985-00-906-3287

Waveguide Adapter - Page 2 of 2



M		

Aluminum alloy single tubing segment and flange

**Style Designator:** 

Waveguide to coaxial

**Supplementary Features:** 

Frequency band c

**Fsc Application Data:** 

Radar equipment

Shelf Life:

N/a

**Unit Of Measure:** 

--

Demilitarization:

Yes - demil/mli

Fiig:

A073a0