## NSN 5985-01-102-0990

Waveguide Adapter - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5985-01-102-0990
Cross Sectional Shape:
Internal, rectangular double ridged external, rectangular
Tubing Wall Construction Style:
Seamless single tubing segment
Flange Quantity:
1
Flange Connecting Hole Diameter:
0.128 inches single flange all connection facilities and 0.130 inches single flange all connection facilities
Voltage Standing Wave Ratio:
1.90
Insertion Loss In Decibels:
0.50
Coaxial Connector Series Designation:
Sma
Connector End Design:
Female
Adapter Length:
2.500 inches
Waveguide Outside Width:
Between 0.783 inches and 0.799 inches
Waveguide Inside Width:
Between 0.599 inches and 0.615 inches
Waveguide Inside Height:
Between 0.229 inches and 0.245 inches
Waveguide Outside Height:
Between 0.413 inches and 0.429 inches
Flange Connecting Facility And Quantity:
2 unthreaded hole single flange all connection facilities
Material:
Copper alloy single tubing segment
Surface Treatment:
Lacquer single flange outside surfaces
Style Designator:
Waveguide to coaxial
Fsc Application Data:
Antennas, waveguides, and related equipment
Shelf Life:
N/a
Unit Of Measure:
<b></b>

Demilitarization:

Yes - demil/mli

## **NSN 5985-01-102-0990** Waveguide Adapter - Page 2 of 2



Fiig:

A073a0