# NSN 5985-01-110-1788

Waveguide Adapter - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5985-01-110-1788

# Cross Sectional Shape:

Internal, rectangular external, rectangular

# Tubing Wall Construction Style:

Seamless single tubing segment

# Flange Quantity:

1

### Flange Inside Width:

0.705 inches single flange and 0.707 inches single flange

# Flange Inside Height:

0.394 inches single flange and 0.396 inches single flange

# Flange Outside Width:

1.298 inches single flange and 1.328 inches single flange

# Flange Outside Height:

1.298 inches single flange and 1.328 inches single flange

#### Flange Depth:

0.298 inches single flange and 0.328 inches single flange

# Flange Connecting Hole Diameter:

0.144 inches single flange all connection facilities and 0.147 inches single flange all connection facilities

# Voltage Standing Wave Ratio:

2.00

# **Coaxial Connector Series Designation:**

Sma

#### Connector End Design:

Female

#### Adapter Length:

Between 1.230 inches and 1.270 inches

# Adapter Height:

Between 1.298 inches and 1.328 inches

# Waveguide Outside Width:

0.702 inches

# Waveguide Inside Width:

0.622 inches

#### Waveguide Inside Height:

0.311 inches

# Waveguide Outside Height:

0.391 inches

# Flange Connecting Facility And Quantity:

4 unthreaded hole single flange all connection facilities

# Flange Style:

Cover type single flange

# Adapterwidth:

Between 1.298 inches and 1.328 inches

# NSN 5985-01-110-1788

Waveguide Adapter - Page 2 of 2

Material:

Copper alloy single flange

Style Designator:

Waveguide to coaxial

**Fsc Application Data:** 

Antennas, waveguides, and related equipment

Shelf Life:

N/a

Unit Of Measure:

---

# Demilitarization:

Yes - demil/mli

Fiig:

A073a0

