

View Online at <https://aerobasegroup.com/nsn/5985-01-234-2114>

End Application:

Radar set an/fps-118

Special Features:

1.640 in. Maximum w; 1.125 in. H; freq: 2 to 32 mhz; impedance: 50 ohm; coupling: two-way (-3 db) power divider; isolation: 20 db min; amplitude balance: 0.5 db max; phase balance: 90 deg, porm 3 deg; insertion loss: 0.7 db max; vswr: 1.2 max; power, input: 1.0 watt; temp, oper: -34 degrees c to +51 degrees c; connector: four bnc female coaxial

Shelf Life:

N/a

Unit Of Measure:

--

Demilitarization:

Yes - demil/mli

Fiig:

A512n0