

View Online at <https://aerobasegroup.com/nsn/5990-00-075-7508>

Fragility Factor:

Moderately rugged

Body Size:

15

Stator Input Voltage Rating In Volts:

16.0

Stator Input Current Rating:

7.0 milliamperes

Stator Input Electrical Power Rating:

35.0 milliwatts

Frequency In Hertz:

400.0

Rotor Dc Resistance In Ohms:

215.00

Stator Dc Resistance In Ohms:

310.00

Compensation Method:

Winding compensated

Compensator Dc Resistance In Ohms:

310.00

Phase Shift Angle In Deg:

5.000 input to output

Maximum Fundamental Null Voltage In Millivolts Per Volt:

10.00 output

Maximum Total Null Voltage Output In Millivolts Per Volt:

20.00

Interaxis Error Angular Range In Minutes:

-5.0/+5.0

Terminal Location:

Rear

Transformation Ratio:

0.980 rotor to stator

Terminal Type And Quantity:

12 screw

Shelf Life:

N/a

Unit Of Measure:

--

Demilitarization:

No

Fig:

A07800