## NSN 5990-00-133-0102

Transmitter Synchro - Page 1 of 2

**Body Material:** 



View Online at https://aerobasegroup.com/nsn/5990-00-133-0102

Any acceptable
Body Style:
Standard round, rotatable housing
Shoulder Diameter:
Between 0.6245 inches and 0.6255 inches
Overall Length:
1.9750 inches
Flange Diameter:
Between 1.0610 inches and 1.0620 inches
Flange Thickness:
0.0930 inches
Body Diameter:
1.0620 inches
Shaft Diameter:
0.1195 inches single shaft and 0.1200 inches single shaft
Shaft Length:
0.3130 inches single shaft
Schematic Diagram Designator:
1 y-rotor, 1 stator
Body Size:
11
Rotor Input Voltage Rating In Volts:
26.0
Frequency In Hertz:
400.0
Rotor Input Current Rating:
240.0 milliamperes
Rotor Input Electrical Power Rating:
920.0 milliwatts
Zro Resistance In Ohms:
16.00
Zso Resistance In Ohms:
5.70
Rotor Dc Resistance In Ohms:
8.50
Stator Dc Resistance In Ohms:
3.00
Phase Shift Angle In Deg:
5.000 input to output
Electrical Error Angular Range In Minutes:
-7.0 to 7.0

## **NSN 5990-00-133-0102** Transmitter Synchro - Page 2 of 2



Actuator Friction Torque At Minus 55 Deg Celsius:
9.0 centimeter-grams
Actuator Friction Torque At Plus 25 Deg Celsius:
3.0 centimeter-grams
Torque Gradient Per Angular Deg:
5700.0 millimeter-milligrams
Alignment Hole Quantity:
4
Shaft Maximum Radial Play:
0.0005 inches
Shaft End Play:
Between 0.0003 inches and 0.0008 inches
Shoulder Length:
Between 0.0590 inches and 0.0650 inches
Mounting Surface To Terminal End Distance:
1.4450 inches
Shaft Maximum Runout:
0.0010 inches
Terminal Location:
Rear
Plus J Zro Reactance In Ohms:
107.00
Shaft Slot Depth:
0.0220 inches single shaft and 0.0320 inches single shaft
Plus J Zso Reactance In Ohms:
18.10
Shaft Slot Width:
0.0220 inches single shaft and 0.0320 inches single shaft
Shaft Type:
Round, slotted single shaft
Alignment Hole Depth:
0.0700 inches
Alignment Hole Bolt Circle Diameter:
Between 0.8090 inches and 0.8150 inches
Terminal Type And Quantity:
5 wire lead
Shelf Life:
N/a
Unit Of Measure:
Demilitarization:
No

Fiig: A07800