

View Online at <https://aerobasegroup.com/nsn/5990-00-402-4901>

Body Material:

Any acceptable

Body Style:

Standard round a

Pilot Diameter:

Between 0.4995 inches and 0.5000 inches

Overall Length:

1.7810 inches

Flange Diameter:

0.7550 inches

Flange Thickness:

0.0620 inches

Undercut Diameter:

0.6910 inches

Undercut Width:

0.0570 inches

Shaft Diameter:

0.0895 inches single shaft and 0.0900 inches single shaft

Shaft Length:

0.5400 inches single shaft

Body Size:

8

Rotor Input Voltage Rating In Volts:

11.8

Frequency In Hertz:

800.0

Rotor Input Current Rating:

43.0 milliamperes

Rotor Input Electrical Power Rating:

120.0 allqjaa3.500 finished-chamfered

Zro Resistance In Ohms:

72.00

Zso Resistance In Ohms:

82.00

Zrs Resistance In Ohms:

81.00

Zss Resistance In Ohms:

101.00

Rotor Dc Resistance In Ohms:

51.00

Stator Dc Resistance In Ohms:

49.50

Phase Shift Angle In Deg:

10.500 input to output

Interaxis Error Angular Range In Minutes:

-30.0/+30.0

Actuator Friction Torque At Minus 55 Deg Celsius:

9.00 centimeter-grams

Actuator Friction Torque At Plus 25 Deg Celsius:

3.00 centimeter-grams

Shaft Radial Play Test Point:

0.120 inches

Shaft Maximum Radial Play:

0.0008 inches

Shaft End Play:

Between 0.0003 inches and 0.0015 inches

Pilot Length:

0.0430 inches

Mounting Surface To Terminal End Distance:

1.2410 inches

Terminal Location:

Rear

Plus J Zro Reactance In Ohms:

270.00

Shaft Slot Depth:

0.0200 inches single shaft and 0.0350 inches single shaft

Plus J Zso Reactance In Ohms:

342.00

Shaft Slot Width:

0.0150 inches single shaft and 0.0300 inches single shaft

Plus J Zrs Reactance In Ohms:

27.00

Shaft Type:

Round, slotted single shaft

Plus J Zss Reactance In Ohms:

37.00

Transformation Ratio:

1.022 rotor to stator

Shaft Radial Play Determining Weight:

4.0 ounces

Shaft End Play Determining Weight:

8.0 ounces

Terminal Type And Quantity:

7 wire lead

Shelf Life:

N/a

Unit Of Measure:

--

Demilitarization:

Yes - demil/mli

Fig:

A07800