

NSN 5990-00-557-3669 Control Transformer Synchro - Page 1 of 2 View Online at https://aerobasegroup.com/nsn/5990-00-557-3669 **Body Material:** Steel, stainless **Body Style:** Standard round b **Shoulder Diameter:** Between 0.1195 inches and 0.1200 inches **Pilot Diameter:** 0.5000 inches **Overall Length:** 1.5150 inches Flange Diameter: Between 1.3100 inches and 1.3140 inches Flange Thickness: Between 0.0620 inches and 0.0650 inches **Undercut Width:** Between 0.0750 inches and 0.0780 inches **Shaft Diameter:** 0.1195 inches single shaft and 0.1200 inches single shaft **Shaft Length:** 0.5000 inches single shaft **Fragility Factor:** Moderately rugged **Body Size:** 14 **Stator Input Voltage Rating In Volts:** 9.0 **Stator Input Current Rating:** 175.0 milliamperes

Stator Input Electrical Power Rating:

100.0 milliwatts

Frequency In Hertz:

400.0

Zro Resistance In Ohms:

6150.00

Zso Resistance In Ohms:

30.00

Zrs Resistance In Ohms:

130.00

Rotor Dc Resistance In Ohms:

670.00

Stator Dc Resistance In Ohms:

41.00

NSN 5990-00-557-3669

Control Transformer Synchro - Page 2 of 2



Phase Shift Angle In Deg: 5.000 input to output Maximum Fundamental Null Voltage In Millivolts Per Volt: 30.00 input Maximum Total Null Voltage Output In Millivolts Per Volt: 70.00 **Electrical Error Angular Range In Minutes:** -45.0/+45.0 **Actuator Friction Torque At Minus 55 Deg Celsius:** 16.0 centimeter-grams **Actuator Friction Torque At Plus 25 Deg Celsius:** 6.0 centimeter-grams Pilot Length: 1.2177 inches **Shoulder Length:** Between 0.0930 inches and 0.0960 inches **Mounting Surface To Terminal End Distance:** Between 1.1080 inches and 1.1110 inches **Terminal Location:** Rear Plus J Zro Reactance In Ohms: 615.00 Plus J Zso Reactance In Ohms: 155.00 Plus J Zrs Reactance In Ohms: 50.00 **Shaft Type:** Round single shaft **Transformation Ratio:** 0.862 rotor to stator **Terminal Type And Quantity:** 5 wire lead Shelf Life: N/a **Unit Of Measure: Demilitarization:** No Fiig: A07800