NSN 5990-00-734-3818

Transmitter Synchro - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/5990-00-734-3818

Body Material:
Steel, stainless
Body Style:
Round, square mounting flange
Overall Length:
1.7960 inches
Flange Thickness:
0.1250 inches
Shaft Diameter:
0.0900 inches both shafts
Shaft Length:
0.3750 inches rear shaft
Fragility Factor:
Moderately rugged
Flange Length:
0.7500 inches
Flange Width:
0.7500 inches
Securing Hole Quantity:
4
Body Size:
8
Rotor Input Voltage Rating In Volts:
25.0
Frequency In Hertz:
400.0
Rotor Input Current Rating:
170.0 milliamperes
Data de Africa de la Decembra de la Companya de la
Rotor Input Electrical Power Rating:
930.0 milliwatts
· · · · · · · · · · · · · · · · · · ·
930.0 milliwatts
930.0 milliwatts Zro Resistance In Ohms:
930.0 milliwatts Zro Resistance In Ohms: 220.00
930.0 milliwatts Zro Resistance In Ohms: 220.00 Mounting Surface To Terminal End Distance:
930.0 milliwatts Zro Resistance In Ohms: 220.00 Mounting Surface To Terminal End Distance: 1.6590 inches
930.0 milliwatts Zro Resistance In Ohms: 220.00 Mounting Surface To Terminal End Distance: 1.6590 inches Terminal Location:
930.0 milliwatts Zro Resistance In Ohms: 220.00 Mounting Surface To Terminal End Distance: 1.6590 inches Terminal Location: Rear
930.0 milliwatts Zro Resistance In Ohms: 220.00 Mounting Surface To Terminal End Distance: 1.6590 inches Terminal Location: Rear Plus J Zro Reactance In Ohms:
930.0 milliwatts Zro Resistance In Ohms: 220.00 Mounting Surface To Terminal End Distance: 1.6590 inches Terminal Location: Rear Plus J Zro Reactance In Ohms: 990.00
930.0 milliwatts Zro Resistance In Ohms: 220.00 Mounting Surface To Terminal End Distance: 1.6590 inches Terminal Location: Rear Plus J Zro Reactance In Ohms: 990.00 Shaft Slot Depth:

NSN 5990-00-734-3818 Transmitter Synchro - Page 2 of 2



Snart Type:
Round both shafts
Securing Hole Bolt Circle Diameter:
0.6090 inches
Terminal Type And Quantity:
5 wire lead
Shelf Life:
N/a
Unit Of Measure:
Demilitarization:
No

Fiig: A07800