NSN 5990-00-810-1518

Body Material:

106.00

Control Transformer Synchro - Page 1 of 3



View Online at https://aerobasegroup.com/nsn/5990-00-810-1518

Steel, stainless **Body Style:** Standard round, rotatable stator c **Shoulder Diameter:** Between 0.9995 inches and 1.0000 inches **Pilot Diameter:** 0.6250 inches **Overall Length:** Between 2.9630 inches and 3.0450 inches Flange Diameter: Between 1.1850 inches and 1.1910 inches Flange Thickness: Between 0.0900 inches and 0.0960 inches **Undercut Diameter:** Between 1.1050 inches and 1.1130 inches **Undercut Width:** 0.0500 inches **Shaft Diameter:** 0.1195 inches front shaft and 0.1200 inches front shaft **Shaft Length:** 0.3950 inches front shaft **Fragility Factor:** Moderately rugged **Body Size:** 12 **Stator Input Voltage Rating In Volts: Stator Input Current Rating:** 21.0 milliamperes **Stator Input Electrical Power Rating:** 50.0 milliwatts Frequency In Hertz: 400.0 **Zro Resistance In Ohms:** 625.00 **Zso Resistance In Ohms:** 93.00 **Zrs Resistance In Ohms:** 570.00 **Zss Resistance In Ohms:**

NSN 5990-00-810-1518

Control Transformer Synchro - Page 2 of 3



Rotor Dc Resistance In Ohms: 385.00 Stator Dc Resistance In Ohms: 60.00 Phase Shift Angle In Deg: 4.200 output to input Maximum Fundamental Null Voltage In Millivolts Per Volt: 34.00 input Maximum Total Null Voltage Output In Millivolts Per Volt: 53.00 **Electrical Error Angular Range In Minutes:** -10.0/+10.0 **Actuator Friction Torque At Minus 55 Deg Celsius:** 120.0 centimeter-grams **Actuator Friction Torque At Plus 25 Deg Celsius:** 30.0 centimeter-grams **Shaft Radial Play Test Point:** 0.125 inches **Shaft Maximum Radial Play:** 0.0050 inches **Shaft End Play:** Between 0.0003 inches and 0.0005 inches **Pilot Length:** 0.0590 mils and 0.0650 centimeters **Shoulder Length:** 0.0590 mils and 0.0650 centimeters **Mounting Surface To Terminal End Distance:** 2.3110 inches **Shaft Maximum Runout:** 0.0010 inches **Terminal Location:** Rear Plus J Zro Reactance In Ohms: 3280.00 Plus J Zso Reactance In Ohms: 570.00 Plus J Zrs Reactance In Ohms: 330.00 **Shaft Type:** Round both shafts Plus J Zss Reactance In Ohms: 68.00

2.203 rotor to stator

Transformation Ratio:

NSN 5990-00-810-1518 Control Transformer Synchro - Page 3 of 3



| Shart Radial Play Determining Weight |
|--------------------------------------|
| 4.0 ounces |
| Shaft End Play Determining Weight: |
| 16.0 ounces |
| Terminal Type And Quantity: |
| 5 wire lead |
| Shelf Life: |
| N/a |
| Unit Of Measure: |
| |
| Demilitarization: |
| No |

Fiig: A07800