

View Online at <https://aerobasegroup.com/nsn/5990-00-891-5113>

**Body Material:**

Steel, corrosion resisting

**Body Style:**

Standard round c

**Shoulder Diameter:**

Between 0.9995 inches and 1.0000 inches

**Pilot Diameter:**

Between 0.6245 inches and 0.6250 inches

**Overall Length:**

Between 2.5500 inches and 2.5650 inches

**Flange Diameter:**

Between 1.0570 inches and 1.0650 inches

**Flange Thickness:**

0.0930 inches

**Undercut Diameter:**

0.9750 inches

**Undercut Width:**

0.0620 inches

**Shaft Diameter:**

0.1852 inches single shaft and 0.1872 inches single shaft

**Shaft Length:**

0.5500 inches single shaft and 0.5650 inches single shaft

**Fragility Factor:**

Moderately rugged

**Body Size:**

11

**Stator Input Voltage Rating In Volts:**

26.0

**Frequency In Hertz:**

400.0

**Zso Resistance In Ohms:**

385.00

**Compensation Method:**

Winding compensated

**Compensator Transformation Ratio In Percent:**

0.990 rotor to compensator

**Phase Shift Angle In Deg:**

8.500 input to output

**Maximum Total Null Voltage Output In Millivolts Per Volt:**

10.00

**Interaxis Error Angular Range In Minutes:**

-5.0/+5.0

**Spline Tooth Quantity:**

21 single shaft

**Alignment Hole Quantity:**

4

**Pilot Length:**

0.0620 inches

**Shoulder Length:**

0.0620 inches

**Mounting Surface To Terminal End Distance:**

2.0000 inches

**Spline Tooth Diametral Pitch:**

120 single shaft

**Shaft Thread Series Designator:**

Unf single shaft

**Shaft Thread Direction:**

Right-hand single shaft

**Shaft Thread Class:**

2a single shaft

**Terminal Location:**

Rear

**Shaft Thread Length:**

0.1900 inches single shaft

**Plus J Zso Reactance In Ohms:**

1960.00

**Shaft Type:**

Spline w/threads single shaft

**Transformation Ratio:**

0.975 rotor to stator

**Alignment Hole Bolt Circle Diameter:**

0.8120 inches

**Shaft Thread Size:**

0.190 inches single shaft

**Terminal Type And Quantity:**

12 screw

**Shelf Life:**

N/a

**Unit Of Measure:**

--

**Demilitarization:**

No

**Fiig:**

A07800