## NSN 5996-01-465-5369

Radio Frequency Amplifier - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/5996-01-465-5369 **Overall Length:** 394.0 millimeters **Overall Height:** 178.0 millimeters Overall Width: 264.0 millimeters **Average Life Measurement:** Not rated **End Application:** An/vrc-516 radio set **Basic Shape Style:** Rectangular or square **Inclosure Type:** Encased Installation Design: Mobile **Circuit Construction Type:** Solid state Frequency Per Channel: 1.6 megahertz operating channel and 59.9 megahertz operating channel **External Dc Operating Voltage In Volts:** 24.0 single voltage and 28.0 single voltage **Special Features:** Speaker on/off switch; circuit breaker reset switch; built-in-test via the receiver-transmitter rt-1694 (p); rf power gain greater than 35 db from 1.6mhz to 29.9 mhz, greater than 30 db from 30 mhz to 59.9 mhz; rf output 150w, 60w, 12w selectable; power level feedback 4.3 v porm 10 pct. For 150w pep output **Functional Description:** Automatically responds to control inputs from the receiver-transmitter, radio rt-1694 (p) and provides 150 w pep/avg. 1.6 to 29.9 mhz, 60 w from 30 to 59.9 mhz **Relationship To Similar Equipment:** One way interchangeable with am-7532/u; the am-7532a/u has the addition of a pre/post selector module that increases the hf performance Shelf Life: N/a **Unit Of Measure: Demilitarization:** 

Yes - demil/mli

Fiig:

A32200