

View Online at <https://aerobasegroup.com/nsn/5996-01-569-0179>

Reliability Indicator:

Not established

Operating Temperature Range:

-30.0/+60.0 degrees celsius

Average Life Measurement:

Not rated

End Application:

H18kec9pw5- (78205) , radio set astro xts 5000

Inclosure Type:

Encased

Installation Design:

Mobile

Circuit Construction Type:

Solid state

Frequency Per Channel:

136.0 megahertz operating channel err-100 and 174.0 megahertz operating channel err-100

Average Power Rating Per Channel:

6.0 watts input

Product Name:

Mobile rf power amplifier

Special Features:

Vhf standard comm. Band; 7 amps ; 10 amp fuse; fm oper. Mode; oper. Voltage: 11 vdc min. 16.6 vdc max; connectors: mini uhf on rf input and output, cinch 4 pin (male) dc input

Shelf Life:

N/a

Unit Of Measure:

--

Demilitarization:

Yes - demil/mli

Fig:

A32200