NSN 6105-01-169-5989

Alternating Current Motor - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/6105-01-169-5989

Shaft Rotation Direction:
Clockwise single end or counterclockwise single end
Duty Cycle:
Continuous
Inclosure Feature:
Totally enclosed
Mounting Method:
Resilient ring
Cooling Method:
Fan cooled
Current Rating Method:
Load
Inclosure Specificationification:
Nema
Frame Size Designation:
48
Power Rating:
0.250 horsepower output
Tempurature Rating:
40.0 ambient degrees celsius
Rotor Speed Rating In Rpm:
Rotor Speed Rating In Rpm: 1725.0 single full load
-
1725.0 single full load
1725.0 single full load Current Rating In Amps:
1725.0 single full load Current Rating In Amps: 5.400 single input
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts:
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic:
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic: A9 single style single end
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic: A9 single style single end Phase:
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic: A9 single style single end Phase: Single input
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic: A9 single style single end Phase: Single input Frequency In Hertz:
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic: A9 single style single end Phase: Single input Frequency In Hertz: 60.0 input
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic: A9 single style single end Phase: Single input Frequency In Hertz: 60.0 input Shelf Life:
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic: A9 single style single end Phase: Single input Frequency In Hertz: 60.0 input Shelf Life: N/a
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic: A9 single style single end Phase: Single input Frequency In Hertz: 60.0 input Shelf Life: N/a
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic: A9 single style single end Phase: Single input Frequency In Hertz: 60.0 input Shelf Life: N/a Unit Of Measure:
1725.0 single full load Current Rating In Amps: 5.400 single input Connection Type And Voltage Rating In Volts: 115.0 line to neutral single input Shaft End Characteristic: A9 single style single end Phase: Single input Frequency In Hertz: 60.0 input Shelf Life: N/a Unit Of Measure: Demilitarization: